


2000 - 6000 MHz

Product Code: LPDA-A0160

VERSION: 1.3





SPECIFICATIONS:

Electrical:	
Frequency range	2000 – 6000 MHz
VSWR	< 2.0:1
Nominal input impedance	50 Ω
Connector	N-type female
Feed power handling	See graph below
Gain (typical)	Typical > 9.5 dBi (see graph below)
E-plane 3 dB beamwidth	45°
H-plane 3 dB beamwidth	60°
Polarisation	Linear
Front-to-back ratio	≥ 15 dB
Mechanical:	
Dimensions (w x I)	106 mm x 332 mm
	(See drawing below)
Material	Aluminium, Brass, Stainless steel,
	Tufnol, FR4
Mass:	
Antenna	< 700 g
Bracket	< 450 g
Environmental: designed	to meet the following specifications
Wind survival	160 km/h calculated
Operating Temperature	-30°C to +65° (no icing)
Storage Temperature	-40°C to +85°
Corrosion	Designed for MIL-STD-810F MIL- 1250A

PRODUCT DESCRIPTION:

The LPDA-A0160 directional log-periodic dipole array (LPDA) is primarily designed for high-power applications. It covers a frequency band of 2000 to 6000 MHz with a gain of greater than 9.5 dBi.

The antenna is completely encapsulated in a radome.

PRODUCT FEATURES:

- Wideband frequency 2000 to 6000 MHz
- Compact size
- VSWR < 2.0:1
- High gain: 9.5 dBi
- Rugged construction
- · Ice resistant

PRODUCT APPLICATIONS:

- Wideband
- High-Power

sales@alaris.co.za


www.alarisantennas.com

GAIN THE ADVANTAGE


2000 - 6000 MHz

Product Code: LPDA-A0160 VERSION: 1.3

Gain:




VSWR:



Updated 2022-09-15


sales@alaris.co.za www.alarisantennas.com



2000 - 6000 MHz

Product Code: LPDA-A0160 VERSION: 1.3

POWER HANDLING:




2000 - 6000 MHz


Product Code: LPDA-A0160 VERSION: 1.3

RADIATION PATTERNS:

Normalised H-plane radiation pattern



Normalised E-plane radiation pattern



Updated 2022-09-15


sales@alaris.co.za www.alarisantennas.com


GAIN THE ADVANTAGE

2000 – 6000 MHz

Product Code: LPDA-A0160 VERSION: 1.3

MECHANICAL OUTLINE:





Updated 2022-09-15

sales@alaris.co.za www.alarisantennas.com

GAIN THE ADVANTAGE